

# QUICK REFERENCE GUIDE

**altronic**<sup>®</sup>  
DE-2500 DIGITAL  
CONTROLLER SYSTEM

TIPS AND HINTS TO ASSIST WITH INSTALLATION AND/OR OPERATION

3/26/07

## Quick Keypad Descriptions

- STOP** Manually stops engine and activates the configured output modules.
- RESET** Clears all past faulted points and resets all input and output timers to their preset values.
- TEST** Disables output modules, allows testing of input sensors, and resets the test timer to its preset value.
- CANCEL TIMERS OR ESC** Cancels all timers including test timer.
- VIEW CHAN** Displays the status of any input channel and its label.
- NEXT** Displays **CAPACITY CONTROL** screen.  
Press **NEXT** again from **HOME** screen for **RPM SETPOINT CONTROL**.  
From **VIEW** screen, displays the next process information screen.  
From **MENU** screens, displays the value to be edited.
- VIEW** Displays the process screens and **BAR** graphs.
- ENTER** Used to accept a selection and save a new value in memory.
- ESC** Exit and view channels, information or menu screens at any time.  
Return to previous screen without changing programmed values.
- F2 & F1** Used to “unlock” controller for changes.
- F1** Displays hourmeter and service meter messages. When in this screen use up arrow key to scroll to next hourmeter.
- F2** Press *prior* to pressing **RESET** for time and date of first fault information. Pressing **RESET** before pressing **F2** will erase first fault information.

*This guide is provided to clarify and add information to the Operating Manual, FORM DE-2500 IOI 3-04.*

*Altronic literature can be found at:  
[www.altronicinc.com](http://www.altronicinc.com)  
under **PRODUCTS**.*

# QUICK REFERENCE GUIDE

---

## Edit and Changes

1. Press **MENU**
2. Press **F2** then **F1**
3. Use **NEXT** key or **↑** and **↓** keys to move cursor to select one of the following:
  - Edit Control Values**
  - Edit Safety Shutdown**
  - Hour Meter Function**
  - View Firmware Rev.**
4. Press **ENTER** after selection is made.
5. Repeat step **3** to select from each of these selections.
6. Press **ENTER** after selection is made.
7. Press **ENTER** to move cursor in sub-screens and **↑** and **↓** keys to change values.
8. Press **ENTER** after changes are made. The new values will remain. If they did not take, the original value will come back into view.  
**IF** new values did not take, start over at step **1**.

